



# Infrared LED Lights **Product Lineup**




## Abundant lineup, total of 56 models Available for various applications



## What is Infrared Light?


Infrared light is light that has a wavelength longer than that of visible red light and cannot be seen by the human eye. Compared to visible red light, infrared light has a low scattering rate and high transmittance rate, and therefore is used in imaging which penetrates printed patterns or liquids.




## Merits


	Infrared LED	Regular halogen light
Irradiation heat	Extremely low	Heat-generating
Influence on the workpiece	Small heat damage	Huge heat damage


Irradiation of the Infrared LED includes only the energy of specific region of wavelength, so that the irradiation heat is extremely low compared to the halogen lights and gives less damage on the workpiece.







## Total of 56 Models CCS has an extensive lineup of Infrared Lights.









\* The wavelengths of the LFV3-CP series are different from those of the LFV3 series.

If you need a wavelength of 1,000 nm or more, please contact your CCS sales representative about the custom product.

## Ready for the test with infrared light over 1,000 nm wavelength

CCS is deploying infrared-sensitive CCD cameras in the testing rooms where you can perform workpiece tests directly for yourself using our LED Lights. Please feel free to make an appointment. We are looking forward to helping you.



#### Specifications

ABA-003IR-GE (manufactured by AVALDATA)

- InGaAs sensor
- Wavelength: 950 to 1,700 nm
- 640 × 512 pixels
- Gia-E vision • C mount





Our personalized staff will be happy to suggest the lighting solution for getting optimal images.

## Imaging examples


Various applications utilizing characteristics of the infrared light

#### Imaging the appearance of food container




Light from the surface-mounted LED is scattered inside of the dome-shaped reflective diffusion panel. The scattered light from the wide uniform region is illuminated onto the workpiece surface evenly.

■ HPD2 series




#### Workpiece




Food container

### Visible light Dome Light



Imaging with visible light captures characters and patterns on the container.

#### Infrared HPD2-400IR860



Imaging with infrared light erases the characters and patterns on the container, and captures the turning up of the cover.


\* This workpiece was processed by CCS for sample imaging.

### Imaging the foreign materials in food product



The dot pattern on the surface of the light-guiding diffusion plate controls the diffusion and transmission of the illuminated light. It can illuminate uniform diffused light onto the workpiece.

#### LFX2 series




#### Workpiece




Snack confectionery

#### Visible light Dome Light



It is difficult to capture the foreign materials with visible light imaging.

#### Infrared LFX2-200IR850




Imaging with infrared light cancels the difference in color density and captures the foreign materials.

 $\ensuremath{^*}$  This workpiece was processed by CCS for sample imaging.

### Imaging the foreign materials in disinfectant product



LEDs embedded around the outside of a square light-guiding diffusion plate. Diffused illumination from a flat emitting surface.



#### Workpiece



Disinfectant product

#### Visible light Flat Light




It is difficult to check the inside with visible light imaging.

#### Infrared LFL-100IR940




Imaging with infrared light penetrates the liquid and captures the foreign materials.

### Imaging the appearance of leatherware



By mounting LEDs on a flexible circuit board in a steep angle, it becomes possible to converge light in the center section from a low position.




#### Workpiece




Leatherware

#### Visible light Ring Light



The leather and the threads are of the same color, so that it is difficult to capture the stitching.

#### Infrared LDR2-132IR2-850-LA



Infrared light penetrates the dye to highlight the threads and captures the stitching.

 $<sup>^{\</sup>ast}$  This workpiece was processed by CCS for sample imaging.



## Infrared Lights IR series have been renewed

#### Features

(1) Unified 24 VDC input

All models are 24 VDC input and the same Control Unit is applicable for the Light Unit of equal size, regardless of the LED color such as red, white, blue, green, ultraviolet, and infrared.

(2) Revamped lineup

New size has been supported by the Flat Lights. Coaxial Lights have been changed to the latest LFV3 series.

(3) Improved output (940 nm type)

State of the art LEDs improved the emitting efficiency. Increased output is 1.5 times the output of the previous models. Available for wider range of applications.

## Specifications of the previous IR series (Scheduled to be discontinued)

series Specification	ns of the p	revious	ik series	discontinued)
Model name	Peak wavelength	Input voltage	Power consumption	Weight
LDR2-50IR850	850 nm		3.8 W	50 g
LDR2-50IR940	940 nm		3.0 W	30 g
LDR2-70IR850	850 nm		7.6 W	130 g
LDR2-70IR940	940 nm		7.0 **	100 g
LDR2-90IR850	850 nm		14 W	170 g
LDR2-90IR940	940 nm			170 9
LDR2-74IR850-LA	850 nm		5.7 W	90 g
LDR2-74IR940-LA	940 nm		3.7 W	30 g
LDR2-132IR850-LA	850 nm		16 W	270 g
LDR2-132IR940-LA	940 nm		10 11	270 9
SQR-56IR850	850 nm		3.8 W	80 g
SQR-56IR940	940 nm		0.0 **	00 g
LDL-42X15IR850	850 nm		1.9 W	40 g
LDL-42X15IR940	940 nm		1.0 **	40 g
LDL-74X27IR850	850 nm		6.9 W	80 g
LDL-74X27IR940	940 nm	12 V	0.0 **	9
LDL-82X15IR850	850 nm		3.8 W	60 g
LDL-82X15IR940	940 nm		0.0 **	00 g
LDL-130X15IR850	850 nm		6.1 W	90 g
LDL-130X15IR940	940 nm		6.1 W	
LDL-180X16IR850	850 nm		8.4 W	110 g
LDL-180X16IR940	940 nm		0	9
LDQ-78IR850	850 nm		6.1 W	110 g
LDQ-78IR940	940 nm		0.1 **	110 9
LDQ-150IR850	850 nm		16 W	530 g
LDQ-150IR940	940 nm			555 9
LDL-100X100IR850	850 nm	24 V	21 W	650 g
LDL-100X100IR940	940 nm	2-7 4		000 g
LFL-100IR850	850 nm		5.3 W	220 g
LFL-100IR940	940 nm	12 V	J.J VV	220 g
LFV2-50IR850	850 nm	12 V	8.4 W	260 g
LFV2-50IR940	940 nm		0.4 **	200 g

### Specifications of the latest IR2 series

Series 2 2 2									
Model name	Peak wavelength	Input voltage	Power consumption	Weight	Overdriving(Strobing				
LDR2-50IR2-850	850 nm		3.8 W	50 g	Applicable				
LDR2-50IR2-940	940 nm		0.0 **	00 g	7.551100010				
LDR2-70IR2-850	850 nm		7.6 W	130 g	Applicable				
LDR2-70IR2-940	940 nm		7.0 **	100 9	/ тррпоавіс				
LDR2-90IR2-850	850 nm		14 W	170 g	Applicable				
LDR2-90IR2-940	940 nm			170 9	пррпоавте				
LDR2-74IR2-850-LA	850 nm		6.9 W	90 g	Applicable				
LDR2-74IR2-940-LA	940 nm		0.0 **	oo g	пррпоавте				
LDR2-132IR2-850-LA	850 nm		16 W	270 g	Applicable				
LDR2-132IR2-940-LA	940 nm		10 00	270 g	Аррисавіс				
LDL-42X15IR2-850	850 nm		2.3 W	40 g	Applicable				
LDL-42X15IR2-940	940 nm		Z.J VV	+0 y	Applicable				
LDL-74X27IR2-850	850 nm		6.9 W	80 g	Applicable				
LDL-74X27IR2-940	940 nm		0.9 W	50 g	Applicable				
LDL-82X15IR2-850	850 nm		3.8 W	60.0	Applicable				
LDL-82X15IR2-940	940 nm		3.0 W	60 g	Applicable				
LDL-130X15IR2-850	850 nm		6.1 W	90 g	Applicable				
LDL-130X15IR2-940	940 nm	24 V			Аррисавіс				
LDL-180X15IR2-850	850 nm	24 V	8.4 W	110 g	Applicable				
LDL-180X15IR2-940	940 nm				Applicable				
LDQ-78IR2-850	850 nm		6.1 W	110 g	Applicable				
LDQ-78IR2-940	940 nm								
LDQ-150IR2-850	850 nm		16 W	530 g	Applicable				
LDQ-150IR2-940	940 nm			330 g	Аррисавіс				
LDL-60X60IR2-850	850 nm		7.6.14/	140 ~	Annlinghla				
LDL-60X60IR2-940	940 nm		7.6 W	140 g	Applicable				
LDL-100X100IR2-850	850 nm		21 W	6E0 ~	Applicable				
LDL-100X100IR2-940	940 nm		Z I VV	650 g	Applicable				
LFL-100IR2-850	850 nm		7.6.10/	260 =	Annlingh!				
LFL-100IR2-940	940 nm		7.6 W	260 g	Applicable				
LFV3-CP18IR2-860	860 nm		2.6.14/	70.0	Applicable				
LFV3-CP18IR2-950	950 nm		2.6 W	70 g	Applicable				
LFV3-35IR2-850(A)*1	850 nm		2.4.14	175 -	A == 1; 1-1;				
LFV3-35IR2-940(A)*1	940 nm		3.1 W	175 g	Applicable				
LFV3-50IR2-850(A)*1	850 nm		0.4.W	225 -	Annlingh!				
LFV3-50IR2-940(A)*1	940 nm		9.1 W	335 g	Applicable				
* The wavelengths of the LEV3-CP series are different from those of the LEV3 series									

<sup>\*</sup> The wavelengths of the LFV3-CP series are different from those of the LFV3 series.

Reason: Due to part manufacturer's circumstances, some optical parts were expected to become difficult to obtain. CCS has changed these parts with those of comparable performance. Effect on functions and performance: The functions and performance of the Light Units have not been affected.

Extension cable	CB series, RCB series
Applicable Control Unit	PD2/PSB/BB series

<sup>\*</sup> The LDL-100X100IR850/940 are 24 VDC input.





<sup>\*1</sup> The suffix "(A)" has been added to the end of several model names, e.g. "LFV3-35RI2-850" has been changed to "LFV3-35RI2-850(A)".

Extension cable FCB series, FRCB series

Applicable Control Unit PD3/PD2/POD/PTU2/PSB/BB series, CC-ST-1024

<sup>\*</sup> Refer to the back cover for other specifications

## Dimensions (mm)


### **Ring Lights LDR2** series




Specifications p.5

LDR2-50IR2-850/-940 4 x M3 x 4 (For installation)

#### LDR2-70IR2-850/-940




LDR2-90IR2-850/-940




### **Low-angle Ring Lights LDR2-LA series**



Specifications p.5



#### LDR2-132IR2-850-LA/-940-LA

















## Dimensions (mm)









## Dimensions (mm)


### **Dome Lights HPD2** series





HPD2-75IR860

HPD2-100IR860

HPD2-150IR860











HPD2-200IR860


HPD2-250IR860












Model name	Peak wavelength	Input voltage	Power consumption	Weight	Model name	Peak wavelength	Input voltage	Power consumption	Weight
HPD2-75IR860			12 W	140 g	HPD2-200IR860				460 g
HPD2-100IR860	860 nm	24 V	23 W	160 g	HPD2-250IR860	860 nm	24 V	46 W	650 g
HPD2-150IR860			35 W	285 g	HPD2-400IR860				1,300 g



### **Large Bar Lights HLDL2** series




#### HLDL2-(Emitting surface length)x45IR-DF-N/-W




Model name (Narrow type)	Peak wavelength	Input voltage	Power consumption	Weight	Model name (Wide type)	Peak wavelength	Input voltage	Power consumption	Weight
HLDL2-150X45IR-DF-N			12 W	390 g	HLDL2-150X45IR-DF-W	- 860 nm	24 V	12 W	300 g
HLDL2-300X45IR-DF-N			24 W	770 g	HLDL2-300X45IR-DF-W			24 W	590 g
HLDL2-450X45IR-DF-N			36 W	1,160 g	HLDL2-450X45IR-DF-W			36 W	880 g
HLDL2-600X45IR-DF-N	860 nm	860 nm 24 V	48 W	1,540 g	HLDL2-600X45IR-DF-W			48 W	1,170 g
HLDL2-750X45IR-DF-N	000 11111		60 W	1,930 g	HLDL2-750X45IR-DF-W			60 W	1,460 g
HLDL2-900X45IR-DF-N			72 W	2,310 g	HLDL2-900X45IR-DF-W			72 W	1,750 g
HLDL2-1050X45IR-DF-N		84 W	2,700 g	HLDL2-1050X45IR-DF-W			84 W	2,040 g	
HLDL2-1200X45IR-DF-N			96 W	3,080 g	HLDL2-1200X45IR-DF-W			96 W	2,330 g


#### **Flat Dome Lights** LFX2 series







Model name	Peak wavelength	Input voltage	Power consumption	Weight
LFX2-50IR850			6.6 W	180 g
LFX2-75IR850			14 W	270 g
LFX2-100IR850	850 nm	24 V	14 W	350 g
LFX2-150IR850			20 W	570 g
LFX2-200IR850			27 W	920 g














- \* These data are for reference only. Actual values may vary.
  \*1 You can specify the connector of the Light Unit cable when you place an order. See below for details.

For example, to order the "LDR2-50IR850" with an M12 connector attached, specify the model name as "LDR2-50IR850-M12".

#### 4-pin M12 Socket Connectors



Model name:

standard model name + " -M12 "

Polarity & Signal:

1 · ( + 24 VDC)

2: No Connection

3: (-GND)

4 : No Connection

#### Flying Leads



Model name: standard model name + " -FL "

Polarity & Signal: Anode( + )Brown/ Cathode( - )Blue

Cable Length: 2,000 mm

Please contact your CCS sales representative about the specifications which are not satisfied by the standard products.

#### Example

Wavelength change

Implementing the LEDs to achieve more than 1,000 nm-wavelength

Feel free to contact us about any other requests such as resizing the emitting surface, cable length, installation structure and so on.

CCS is deploying infrared-sensitive CCD cameras in the testing rooms where you can perform workpiece tests directly for yourself using our LED Lights. Please feel free to make an appointment. We are looking forward to helping you.

For using infrared products

#### CAUTION

- Do not expose human eyes to infrared radiation. Also, make known to all personnel concerned the risk of infrared radiation
- When you see the LEDs of the product, you may find some LEDs lit and others do not. This is because irradiation from the LEDs sometimes include visible light. The LED emits infrared radiation even when it seems not to light, so that do not look at the radiating surface of the product directly by the naked eye. To check out the lighting failure of the LED, use a camera to do it by indirect means. You can also check it out through an LCD display of the general-purpose digital camera or mobile phone.
- "CCS", "LIGHTING SOLUTION", "LDR", "LDL", "LDQ", "HLDL", "LFX", "HPD", "LFL", and "LFV" are registered trademarks or trademarks of CCS Inc.

- To ensure proper and safe use of the product, please read the Instruction Guide completely before using the product.
- The design and specifications of this product are subject to change without notification for product improvement.
- The workpiece imaging examples included in this pamphlet are intended to serve only as references to help you select a suitable Light Unit. Please verify the functionality and conditions required for your particular application before you make a final selection. The sample workpieces used in this pamphlet have been processed specifically for sample imaging. They are not intended to represent product quality and performance.



#### Headquarters

Shimodachiuri-agaru, karasuma-dori, kamigyo-ku, Kyoto 602-8011 JAPAN TEL: +81-75-415-8284 / FAX: +81-75-415-8278

URL : http://www.ccs-grp.com/ E-mail: sales@ccs-inc.co.jp

#### **CCS Asia PTE LTD**

63 Hillview Avenue #07-10, Lam Soon Industrial Building, Singapore 669569 TEL: +65-6769-1669 / FAX: +65-6769-3422

URL: http://www.ccs-asia.com.sg/ Email: sales@ccs-asia.com.sq

#### CCS America, Inc.

5 Burlington Woods, Suite 204, Burlington, MA 01803, USA TEL: +1-781-272-6900 / FAX: +1-781-272-6902 URL: http://www.ccsamerica.com/

Email: info@ccsamerica.com

CCS Inc. Shanghai Office Room 308B-309, CIMIC Tower No.1090 Century Avenue, Pu Dong New Area, Shanghai 200120, P.R. China TEL: +86-21-5835-8728 / FAX: +86-21-5835-8928 Email: ccschina@ccs-inc.co.jp

#### CCS Europe NV/SA

Bergensesteenweg 421B,

1600 Sint-Pieters-Leeuw, Belgium TEL: +32-(0)2-333-0080 / FAX: +32-(0)2-333-0081

Email : info@ccseu.com

#### CCS Inc. Shenzhen office

17B,China Economic Trade Building, 7Rd Zizhu, Zhuzilin, Futian District, Shenzhen 518040 P.R.China TEL: +86-755-8279-0477 / FAX: +86-755-8279-0478

Email: ccschina@ccs-inc.co.jp